

# PanelView Plus to PanelView Plus 6 Catalog Number Conversions

| Topic                                | Page |
|--------------------------------------|------|
| About This Publication               | 1    |
| Important Distinctions               | 1    |
| Catalog Number Explanations          | 4    |
| PanelView Plus 6 Product Selections  | 5    |
| PanelView Plus 6 Product Accessories | 6    |
| Catalog Number Conversion Tables     | 8    |
| Additional Resources                 | 21   |

## About This Publication

This publication provides information about the conversion of the PanelView Plus and PanelView Plus CE 700 to 1500 terminals to the new generation PanelView Plus 6 terminals.

## Important Distinctions

There are some important distinctions between the PanelView Plus 6 terminals and the PanelView Plus and PanelView Plus CE 700 to 1500 terminals.

### Product Name

The new generation of HMI terminals is named PanelView Plus 6 terminals. They are available with or without extended features and file viewers. There is no longer a distinction between PanelView Plus and PanelView Plus CE terminals.

- PanelView Plus 6 terminals without extended features, catalog number 2711P-xxxxx8, correlate to catalog numbers 2711P-xxxxx1, 2711P-xxxxx2, and 2711P-xxxxx3 PanelView Plus terminals.
- PanelView Plus 6 terminals with extended features and file viewers, catalog number 2711P-xxxxx9, correlate to catalog numbers 2711P-xxxxx6 and 2711P-xxxxx7 PanelView Plus CE terminals.

## Platform Comparisons

This table compares the platform differences between the new PanelView Plus 6 terminals and the PanelView Plus/PanelView Plus CE terminals.

**Table 1 - PanelView Plus 6 and PanelView Plus Platform Comparison**

| Feature                        | Platform   |  |
|--------------------------------|--|--|
|                                | PanelView Plus 6 Terminals<br>700, 1000, 1250, 1500                    | PanelView Plus and<br>PanelView Plus CE terminals<br>700, 1000, 1250, 1500 |
| FactoryTalk View ME Station    | Version 6.0 or later   | Version 3.20...5.10  |
| FactoryTalk ViewPoint Software | Version 1.2 or later   | Version 1.2 on series E or later terminals, requires 128 MB RAM            |
| Operating system               | Windows CE 6.0 R3  | Windows CE 4.1   |
| Open architecture              | Yes (SDK available)  | (SDK available)  |
| .Net Compact Framework         | Version 3.5  | Version 1.1, not installed   |
| File system                    | Datalight Reliance with FAT support                                    | FAT16, FAT32, on 512 MB version  |
| CPU                            | x86, 1.0 GHz   | x86, Intel Celeron, 650 MHz  |
| FSB                            | 400 MHz  | 100 MHz  |
| RAM                            | 512 MB DDR2 (chip onboard)<br>4264 MiB/s peak                          | 64, 128, 256, or 512 MB,<br>PC100 SDRAM SODIMM<br>800 MiB/s peak           |
| Internal storage               | 512 MB nonvolatile flash<br>(chip onboard)                             | 64, 128, or 256MB  |
| Real-time clock                | Yes  | Yes  |
| Interfaces                     |  |  |
| Secure Digital (SD) slot       | 1 Secure Digital high-capacity (SDHC) slot                             | —  |
| CompactFlash (CF)              | —  | 1 CF Type I  |
| USB                            | 2 USB-A, V2.0 high-speed<br>1 USB min-USB-B, V2.0<br>high-speed, 5-pin | 2 USB-A, V1.1  |
| PCI                            | 1 PCI, 3.3/5V 32-bit   | 1 PCI, 3.3/5V 32-bit   |
| Communication interfaces       |  |  |
| Ethernet                       | (1) 10/100 Mbps,<br>Auto-MDI/MDI-X                                     | (1) 10/100 Mbps  |
| RS-232                         | (1) DB9  | (1) DB9  |
| ControlNet                     | Add-on communication module  | Add-on communication module  |
| Data Highway Plus              | Add-on communication module  | Add-on communication module  |
| DH-485                         | Add-on communication module  | Add-on communication module  |
| Remote I/O                     | —  | Add-on communication module  |
| DeviceNet                      | —  | Add-on communication module  |
| Input power                    | Isolated DC voltage or<br>AC voltage                                   | Isolated DC voltage, non-isolated<br>DC voltage, or AC voltage             |

## Software Versions

All PanelView Plus 6 terminals run the following:

- Windows CE 6.0 operating system
- FactoryTalk View ME software, version 6.0 or later
- FactoryTalk View ME Station software, version 6.0 or later (preloaded and activated)
- FactoryTalk ViewPoint software, version 1.2 or later (single license included with each terminal)

The older PanelView Plus and PanelView Plus CE terminals run the following:

- Windows CE 4.1 operating system
- FactoryTalk View ME software, version 5.10 or earlier
- FactoryTalk View ME Station software, version 5.10 or earlier (preloaded and activated)
- FactoryTalk ViewPoint software, version 1.2 (single license included with each terminal)

## Application Compatibility

HMI applications created in FactoryTalk Studio for Machine Edition software, version 3.2 or later, are compatible and can run on PanelView Plus 6 terminals.

## Logic Modules

PanelView Plus 6 terminals support a new set of logic modules:

- 2711P-RP8x logic modules support PanelView Plus 6 terminals without extended features and file viewers.
- 2711P-RP9x logic modules support PanelView Plus 6 terminals with extended features and file viewers.

**IMPORTANT** Logic modules used with the PanelView Plus and PanelView Plus CE terminals, catalog numbers 2711P-RP, 2711P-RPA, 2711P-RPD, 2711P-RP1x, 2711P-RP2x, 2711P-RP3x, 2711P-RP6x, and 2711P-RP7x, are not compatible with the PanelView Plus 6 terminals.

## Display Modules

All existing 2711P-RDxxxx display modules are compatible with the PanelView Plus 6 terminals except for the following:

- 2711P-RDB7C series A
- 2711P-RDT12C series A
- 2711P-RDB12C series A

For more information, go the knowledgebase at <http://www.rockwellautomation.custhelp.com> and search for ID 115612.


## Catalog Number Explanations


Table 2 and Table 3 show the differences in the catalog number breakdown for the PanelView Plus 6 terminals that will be replacing the PanelView Plus and PanelView Plus CE terminals. All PanelView Plus 6 terminals come standard with 512 MB nonvolatile memory and 512 MB of random-access memory.

**Table 2 - New PanelView Plus 6 Terminals**

| Bulletin Number | Input Type       | Display Size                 | Display Type | Communication                                    | Power  | Operating System   | Special Option       |
|-----------------|------------------|------------------------------|--------------|--|--------|--|----------------------|
| 2711P-          | K = Keypad       | 7 = 6.5 in.                  | C = Color    | 4 = Ethernet, RS-232, (2) USB Host, 1 USB Device | A = AC | 8 = Windows CE 6.0 operating system                        | K = Conformal-coated |
|                 | T = Touch        | 10 = 10.4 in.                |              |  | D = DC | 9 = Windows CE 6.0 operating system with extended features |                      |
|                 | B = Keypad/touch | 12 = 12.1 in.<br>15 = 15 in. |              |  |        |  |                      |

All PanelView Plus 6 terminals run the Windows CE operating system (OS), providing OS elements that meet the majority of user needs. Additional functionality is available by ordering terminals with optional, extended features.

| Standard Features  | Cat. No.<br>2711P-xxxx8<br>2711P-RP8x | Cat. No.<br>2711P-xxxx9<br>2711P-RP9x |
|--|---------------------------------------|---------------------------------------|
| FTP server   | •                                     | •                                     |
| VNC Client/server  | •                                     | •                                     |
| ActiveX controls   | •                                     | •                                     |
| Third-party device support   | •                                     | •                                     |
|  PDF reader | •                                     | •                                     |
| <b>Optional Extended Features</b>  |                                       |                                       |
| Web browser - Internet Explorer  | —                                     | •                                     |
| Remote desktop connection  | —                                     | •                                     |
| Media player   | —                                     | •                                     |
| Microsoft Office file viewers  |                                       |                                       |
| • PowerPoint   | —                                     | •                                     |
| • Excel  | —                                     | •                                     |
| • Word   | —                                     | •                                     |
| WordPad text editor  | —                                     | •                                     |



**Table 3 - PanelView Plus and PanelView Plus CE Terminals**

| Bulletin Number | Input Type       | Display Size  | Display Type                    | Communication                  | Power  | Logic Module with Flash and RAM Memory | Special Option       |
|-----------------|------------------|---------------|---------------------------------|--------------------------------|--------|--|----------------------|
| 2711P-          | K = Keypad       | 7 = 6.5 in.   | C = Color                       | 4 = Ethernet, RS-232 & (2) USB | A = AC | 1 = Logic module 64 MB                 | K = Conformal-coated |
|                 | T = Touch        | 10 = 10.4 in. |                                 |                                | D = DC | 2 = Logic module 128 MB                |                      |
|                 | B = Keypad/touch | 12 = 12.1 in. | 6 = CE Logic module with 128 MB |                                |        |  |                      |
|                 |                  | 15 = 15 in.   | 7 = CE Logic module with 256 MB |                                |        |  |                      |

## PanelView Plus 6 Product Selections

[Table 4](#) and [Table 5](#) list the catalog numbers available for the PanelView Plus 6 terminals. These catalog numbers are referenced in the [Catalog Number Conversion Tables](#) starting on page [8](#).

**Table 4 - PanelView Plus 6 Terminals without Extended Features**

| Cat. No.          |                               |               | Display |       | Communication |          | Input Power | Nonvolatile Flash/RAM Memory |
|-------------------|-------------------------------|---------------|---------|-------|---------------|----------|-------------|------------------------------|
| Keypad            | Touch                         | Keypad/Touch  | Size    | Type  | RS-232        | Ethernet |             |                              |
| <b>700 Model</b>  |                               |               |         |       |               |          |             |                              |
| 2711P-K7C4D8      | 2711P-T7C4D8                  | 2711P-B7C4D8  | 6.5-in. | Color | •             | •        | DC          | 512 MB/512 MB                |
| –                 | 2711P-T7C4D8K <sup>(1)</sup>  | –             |         |       | •             | •        | DC          | 512 MB/512 MB                |
| 2711P-K7C4A8      | 2711P-T7C4A8                  | 2711P-B7C4A8  |         |       | •             | •        | AC          | 512 MB/512 MB                |
| <b>1000 Model</b> |                               |               |         |       |               |          |             |                              |
| 2711P-K10C4D8     | 2711P-T10C4D8                 | 2711P-B10C4D8 | 10.4-in | Color | •             | •        | DC          | 512 MB/512 MB                |
| 2711P-K10C4A8     | 2711P-T10C4A8                 | 2711P-B10C4A8 |         |       | •             | •        | AC          | 512 MB/512 MB                |
| <b>1250 Model</b> |                               |               |         |       |               |          |             |                              |
| 2711P-K12C4D8     | 2711P-T12C4D8                 | 2711P-B12C4D8 | 12.1-in | Color | •             | •        | DC          | 512 MB/512 MB                |
| –                 | 2711P-T12C4D8K <sup>(1)</sup> | –             |         |       | •             | •        | DC          | 512 MB/512 MB                |
| 2711P-K12C4A8     | 2711P-T12C4A8                 | 2711P-B12C4A8 |         |       | •             | •        | AC          | 512 MB/512 MB                |
| <b>1500 Model</b> |                               |               |         |       |               |          |             |                              |
| 2711P-K15C4D8     | 2711P-T15C4D8                 | 2711P-B15C4D8 | 15-in.  | Color | •             | •        | DC          | 512 MB/512 MB                |
| 2711P-K15C4A8     | 2711P-T15C4A8                 | 2711P-B15C4A8 |         |       | •             | •        | AC          | 512 MB/512 MB                |

(1) Conformal-coated terminal.

**Table 5 - PanelView Plus 6 Terminals with Extended Features**

| Cat. No.          |               |               | Display |       | Communication |          | Input Power | Nonvolatile Flash/RAM Memory |
|-------------------|---------------|---------------|---------|-------|---------------|----------|-------------|------------------------------|
| Keypad            | Touch         | Keypad/Touch  | Size    | Type  | RS-232        | Ethernet |             |                              |
| <b>700 Model</b>  |               |               |         |       |               |          |             |                              |
| 2711P-K7C4D9      | 2711P-T7C4D9  | 2711P-B7C4D9  | 6.5-in. | Color | •             | •        | DC          | 512 MB/512 MB                |
| 2711P-K7C4A9      | 2711P-T7C4A9  | 2711P-B7C4A9  |         |       | •             | •        | AC          | 512 MB/512 MB                |
| <b>1000 Model</b> |               |               |         |       |               |          |             |                              |
| 2711P-K10C4D9     | 2711P-T10C4D9 | 2711P-B10C4D9 | 10.4-in | Color | •             | •        | DC          | 512 MB/512 MB                |
| 2711P-K10C4A9     | 2711P-T10C4A9 | 2711P-B10C4A9 |         |       | •             | •        | AC          | 512 MB/512 MB                |
| <b>1250 Model</b> |               |               |         |       |               |          |             |                              |
| 2711P-K12C4D9     | 2711P-T12C4D9 | 2711P-B12C4D9 | 12.1-in | Color | •             | •        | DC          | 512 MB/512 MB                |
| 2711P-K12C4A9     | 2711P-T12C4A9 | 2711P-B12C4A9 |         |       | •             | •        | AC          | 512 MB/512 MB                |
| <b>1500 Model</b> |               |               |         |       |               |          |             |                              |
| 2711P-K15C4D9     | 2711P-T15C4D9 | 2711P-B15C4D9 | 15-in.  | Color | •             | •        | DC          | 512 MB/512 MB                |
| 2711P-K15C4A9     | 2711P-T15C4A9 | 2711P-B15C4A9 |         |       | •             | •        | AC          | 512 MB/512 MB                |

## PanelView Plus 6 Product Accessories

New catalog numbers are available for PanelView Plus 6 logic modules and Secure Digital (SD) memory cards. The display modules in [Table 8](#) and the communication modules in [Table 9](#) can be used with all PanelView Plus 6 terminals.

**Table 6 - Logic Modules**

| Cat. No.                                       | Power Input | Nonvolatile Flash/RAM | Communication  | Marine Certified | Conformal Coated | Included Software  |
|--|-------------|-----------------------|--|------------------|------------------|--|
| <b>Logic Modules without Extended Features</b> |             |                       |  |                  |                  |  |
| 2711P-RP8A                                     | AC          | 512/512 MB            | <ul style="list-style-type: none"> <li>Ethernet</li> <li>RS-232</li> <li>Network interface for communication module</li> </ul> | •                |                  | <ul style="list-style-type: none"> <li>Windows CE 6.0 operating system without extended features/file viewers</li> <li>FactoryTalk View Machine Edition runtime, version 6.0 or later</li> <li>FactoryTalk ViewPoint software, version 1.2 or later</li> </ul> |
| 2711P-RP8D                                     | DC          | 512/512 MB            |  | •                |                  |  |
| 2711P-RP8DK                                    | DC          | 512/512 MB            |  | •                | •                |  |
| <b>Logic Modules with Extended Features</b>    |             |                       |  |                  |                  |  |
| 2711P-RP9A                                     | AC          | 512/512 MB            | <ul style="list-style-type: none"> <li>Ethernet</li> <li>RS-232</li> <li>Network interface communication module</li> </ul>     | •                |                  | <ul style="list-style-type: none"> <li>Windows CE 6.0 operating system with extended features/file viewers</li> <li>FactoryTalk View Machine Edition runtime, version 6.0 or later</li> <li>FactoryTalk ViewPoint software, version 1.2 or later</li> </ul>    |
| 2711P-RP9D                                     | DC          | 512/512 MB            |  | •                |                  |  |
| 2711P-RP9DK                                    | DC          | 512/512 MB            |  | •                | •                |  |

**Table 7 - Secure Digital (SD) Cards**

| Cat. No.   | Description                                    |
|------------|--|
| 1784-SD1   | 1 GB Secure Digital (SD) card                  |
| 1784-SD2   | 2 GB Secure Digital (SD) card                  |
| 2711C-RCSD | USB to SD adapter for Secure Digital (SD) card |

**Table 8 - Display Modules**

| Cat. No.         | Input Type   | Display       | Marine Certified | Conformal Coated | Built-in Antiglare Overlay |
|------------------|--------------|---------------|------------------|------------------|----------------------------|
| <b>700 Model</b> |              |               |                  |                  |                            |
| 2711P-RDK7C      | Keypad       | 7.0-in. color |                  |                  |                            |
| 2711P-RDK7CK     | Keypad       |               |                  | •                |                            |
| 2711P-RDT7C      | Touch        |               |                  |                  |                            |
| 2711P-RDT7CK     | Touch        |               |                  | •                |                            |
| 2711P-RDT7CM     | Touch        |               | •                |                  |                            |
| 2711P-RDB7C      | Keypad/Touch |               |                  |                  |                            |
| 2711P-RDB7CK     | Keypad/Touch |               |                  | •                |                            |
| 2711P-RDB7CM     | Keypad/Touch |               | •                |                  |                            |

**Table 8 - Display Modules**

| Cat. No.                    | Input Type   | Display        | Marine Certified | Conformal Coated | Built-in Antiglare Overlay |
|-----------------------------|--------------|----------------|------------------|------------------|----------------------------|
| <b>1000 Model</b>           |              |                |                  |                  |                            |
| 2711P-RDK10C                | Keypad       | 10.4-in. color |                  |                  |                            |
| 2711P-RDT10C                | Touch        |                |                  |                  |                            |
| 2711P-RDT10CM               | Touch        |                | •                |                  |                            |
| 2711P-RDB10C                | Keypad/Touch |                |                  |                  |                            |
| 2711P-RDB10CM               | Keypad/Touch |                | •                |                  |                            |
| <b>1250 Model</b>           |              |                |                  |                  |                            |
| 2711P-RDK12C                | Keypad       | 12.1-in. color |                  |                  |                            |
| 2711P-RDK12CK               | Keypad       |                |                  | •                |                            |
| 2711P-RDT12C                | Touch        |                |                  |                  |                            |
| 2711P-RDT12CK               | Touch        |                |                  | •                |                            |
| 2711P-RDT12AG               | Touch        |                |                  |                  | •                          |
| 2711P-RDT12H <sup>(1)</sup> | Touch        |                |                  |                  |                            |
| 2711P-RDB12C                | Keypad/Touch |                |                  |                  |                            |
| 2711P-RDB12CK               | Keypad/Touch |                |                  | •                |                            |
| <b>1500 Model</b>           |              |                |                  |                  |                            |
| 2711P-RDK15C                | Keypad       | 15.0-in. color |                  |                  |                            |
| 2711P-RDT15C                | Touch        |                |                  |                  |                            |
| 2711P-RDT15AG               | Touch        |                |                  |                  | •                          |
| 2711P-RDB15C                | Keypad/Touch |                |                  |                  |                            |

(1) This catalog number is a high-bright display module, indicated by the H at end of the cat. no., that is designed for outdoor applications. The high-bright display module can be used only with DC-powered logic modules.

**Table 9 - Communication Modules**

| Cat. No.     | Communication |        |                           | Conformal Coated | Marine Certified |
|--------------|---------------|--------|---------------------------|------------------|------------------|
|              | DH+           | DH-485 | ControlNet <sup>(1)</sup> |                  |                  |
| 2711P-RN6    | •             | •      |                           |                  |                  |
| 2711P-RN6K   | •             | •      |                           | •                |                  |
| 2711P-RN15S  |               |        | •                         |                  | •                |
| 2711P-RN15SK |               |        | •                         | •                |                  |

(1) Scheduled and unscheduled communication.

## Catalog Number Conversion Tables

Tables 10...13 assist you in selecting a PanelView Plus 6 terminal that is equivalent to a PanelView Plus or PanelView Plus CE terminal.

- PanelView Plus 6 catalog numbers ending in 8, without extended features and file viewers, are equivalent to the PanelView Plus terminals.
- PanelView Plus 6 catalog numbers ending in 9, with extended features and file viewers, are equivalent to the PanelView Plus CE terminals.

You can upgrade from a PanelView Plus terminal directly to a PanelView Plus 6 terminal with extended features without any restrictions.

**Table 10 - Cat. No. Conversions for 700 Terminal Models**

| From Existing PanelView Plus/PanelView Plus CE                           | To New PanelView Plus 6 | +            | Communication Module |             |
|--|-------------------------|--------------|----------------------|-------------|
| <b>700 Keypad &amp; Touch-screen Terminals</b>                           |                         |              |                      |             |
| Configured terminal with ControlNet communication                        | 2711P-B7C15A1           | 2711P-B7C4A8 | +                    | 2711P-RN15S |
|  | 2711P-B7C15A2           |              |                      |             |
|  | 2711P-B7C15A6           | 2711P-B7C4A9 | +                    | 2711P-RN15S |
|  | 2711P-B7C15A7           |              |                      |             |
|  | 2711P-B7C15B1           | 2711P-B7C4A8 | +                    | 2711P-RN15S |
|  | 2711P-B7C15B2           |              |                      |             |
|  | 2711P-B7C15D1           | 2711P-B7C4D8 | +                    | 2711P-RN15S |
|  | 2711P-B7C15D2           |              |                      |             |
|  | 2711P-B7C15D6           | 2711P-B7C4D9 | +                    | 2711P-RN15S |
|  | 2711P-B7C15D7           |              |                      |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-B7C4A1            | 2711P-B7C4A8 | +                    | —           |
|  | 2711P-B7C4A2            |              |                      |             |
|  | 2711P-B7C4A6            | 2711P-B7C4A9 | +                    | —           |
|  | 2711P-B7C4A7            |              |                      |             |
|  | 2711P-B7C4B1            | 2711P-B7C4A8 | +                    | —           |
|  | 2711P-B7C4B2            |              |                      |             |
|  | 2711P-B7C4D1            | 2711P-B7C4D8 | +                    | —           |
|  | 2711P-B7C4D2            |              |                      |             |
|  | 2711P-B7C4D6            | 2711P-B7C4D9 | +                    | —           |
|  | 2711P-B7C4D7            |              |                      |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-B7C6A1            | 2711P-B7C4A8 | +                    | 2711P-RN6   |
|  | 2711P-B7C6A2            |              |                      |             |
|  | 2711P-B7C6A6            | 2711P-B7C4A9 | +                    | 2711P-RN6   |
|  | 2711P-B7C6A7            |              |                      |             |
|  | 2711P-B7C6B1            | 2711P-B7C4A8 | +                    | 2711P-RN6   |
|  | 2711P-B7C6B2            |              |                      |             |
|  | 2711P-B7C6D1            | 2711P-B7C4D8 | +                    | 2711P-RN6   |
|  | 2711P-B7C6D2            |              |                      |             |
|  | 2711P-B7C6D6            | 2711P-B7C4D9 | +                    | 2711P-RN6   |
|  | 2711P-B7C6D7            |              |                      |             |



**Table 10 - Cat. No. Conversions for 700 Terminal Models**

| From Existing PanelView Plus/PanelView Plus CE                           | To New PanelView Plus 6                            | +             | Communication Module |             |
|--|--|---------------|----------------------|-------------|
| <b>700 Touch-screen Terminals</b>  |  |               |                      |             |
| Configured terminal with ControlNet communication                        | 2711P-T7C15A1                                      | 2711P-T7C4A8  | +                    | 2711P-RN15S |
|  | 2711P-T7C15A2                                      |               |                      |             |
|  | 2711P-T7C15A6                                      | 2711P-T7C4A9  | +                    | 2711P-RN15S |
|  | 2711P-T7C15A7                                      |               |                      |             |
|  | 2711P-T7C15B1                                      | 2711P-T7C4A8  | +                    | 2711P-RN15S |
|  | 2711P-T7C15B2                                      |               |                      |             |
|  | 2711P-T7C15D1                                      | 2711P-T7C4D8  | +                    | 2711P-RN15S |
|  | 2711P-T7C15D2                                      |               |                      |             |
|  | 2711P-T7C15D6                                      | 2711P-T7C4D9  | +                    | 2711P-RN15S |
|  | 2711P-T7C15D7                                      |               |                      |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-T7C4A1                                       | 2711P-T7C4A8  | +                    | —           |
|  | 2711P-T7C4A2                                       |               |                      |             |
|  | 2711P-T7C4A6                                       | 2711P-T7C4A9  | +                    | —           |
|  | 2711P-T7C4A7                                       |               |                      |             |
|  | 2711P-T7C4B1                                       | 2711P-T7C4A8  | +                    | —           |
|  | 2711P-T7C4B2                                       |               |                      |             |
|  | 2711P-T7C4D1                                       | 2711P-T7C4D8  | +                    | —           |
|  | 2711P-T7C4D2                                       |               |                      |             |
|  | 2711P-T7C4D6                                       | 2711P-T7C4D9  | +                    | —           |
|  | 2711P-T7C4D7                                       |               |                      |             |
|  | 2711P-T7C4D2K                                      | 2711P-T7C4D8K | +                    | —           |
|  | 2711P-T7C4D6K                                      |               |                      |             |
|  | Configured terminal with DH+ /DH-485 communication | 2711P-T7C6A1  | 2711P-T7C4A8         | +           |
| 2711P-T7C6A2   |  |               |                      |             |
| 2711P-T7C6A6   |  | 2711P-T7C4A9  | +                    | 2711P-RN6   |
| 2711P-T7C6A7   |  |               |                      |             |
| 2711P-T7C6B1   |  | 2711P-T7C4A8  | +                    | 2711P-RN6   |
| 2711P-T7C6B2   |  |               |                      |             |
| 2711P-T7C6D1   |  | 2711P-T7C4D8  | +                    | 2711P-RN6   |
| 2711P-T7C6D2   |  |               |                      |             |
| 2711P-T7C6D6   |  | 2711P-T7C4D9  | +                    | 2711P-RN6   |
| 2711P-T7C6D7   |  |               |                      |             |

**Table 10 - Cat. No. Conversions for 700 Terminal Models**

| <b>From Existing PanelView Plus/PanelView Plus CE</b>                    | <b>To New PanelView Plus 6</b> | <b>+</b>     | <b>Add-on Comm Module</b> |             |
|--|--------------------------------|--------------|---------------------------|-------------|
| <b>700 Keypad Terminals</b>  |                                |              |                           |             |
| Configured terminal with ControlNet communication                        | 2711P-K7C15A1                  | 2711P-K7C4A8 | +                         | 2711P-RN15S |
|  | 2711P-K7C15A2                  |              |                           |             |
|  | 2711P-K7C15A6                  | 2711P-K7C4A9 | +                         | 2711P-RN15S |
|  | 2711P-K7C15A7                  |              |                           |             |
|  | 2711P-K7C15B1                  | 2711P-K7C4A8 | +                         | 2711P-RN15S |
|  | 2711P-K7C15B2                  |              |                           |             |
|  | 2711P-K7C15D1                  | 2711P-K7C4D8 | +                         | 2711P-RN15S |
|  | 2711P-K7C15D2                  |              |                           |             |
|  | 2711P-K7C15D6                  | 2711P-K7C4D9 | +                         | 2711P-RN15S |
|  | 2711P-K7C15D7                  |              |                           |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-K7C4A1                   | 2711P-K7C4A8 | +                         | —           |
|  | 2711P-K7C4A2                   |              |                           |             |
|  | 2711P-K7C4A6                   | 2711P-K7C4A9 | +                         | —           |
|  | 2711P-K7C4A7                   |              |                           |             |
|  | 2711P-K7C4B1                   | 2711P-K7C4A8 | +                         | —           |
|  | 2711P-K7C4B2                   |              |                           |             |
|  | 2711P-K7C4D1                   | 2711P-K7C4D8 | +                         | —           |
|  | 2711P-K7C4D2                   |              |                           |             |
|  | 2711P-K7C4D6                   | 2711P-K7C4D9 | +                         | —           |
|  | 2711P-K7C4D7                   |              |                           |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-K7C6A1                   | 2711P-K7C4A8 | +                         | 2711P-RN6   |
|  | 2711P-K7C6A2                   |              |                           |             |
|  | 2711P-K7C6A6                   | 2711P-K7C4A9 | +                         | 2711P-RN6   |
|  | 2711P-K7C6A7                   |              |                           |             |
|  | 2711P-K7C6B1                   | 2711P-K7C4A8 | +                         | 2711P-RN6   |
|  | 2711P-K7C6B2                   |              |                           |             |
|  | 2711P-K7C6D1                   | 2711P-K7C4D8 | +                         | 2711P-RN6   |
|  | 2711P-K7C6D2                   |              |                           |             |
|  | 2711P-K7C6D6                   | 2711P-K7C4D9 | +                         | 2711P-RN6   |
|  | 2711P-K7C6D7                   |              |                           |             |

**Table 11 - Cat. No. Conversions for 1000 Terminal Models**

| From Existing PanelView Plus/PanelView Plus CE                           | To New PanelView Plus 6 | +             | Communication Module |             |
|--|-------------------------|---------------|----------------------|-------------|
| <b>1000 Keypad &amp; Touch-screen Terminals</b>                          |                         |               |                      |             |
| Configured terminal with ControlNet communication                        | 2711P-B10C15A1          | 2711P-B10C4A8 | +                    | 2711P-RN15S |
|  | 2711P-B10C15A2          |               |                      |             |
|  | 2711P-B10C15A6          | 2711P-B10C4A9 | +                    | 2711P-RN15S |
|  | 2711P-B10C15A7          |               |                      |             |
|  | 2711P-B10C15B1          | 2711P-B10C4A8 | +                    | 2711P-RN15S |
|  | 2711P-B10C15B2          |               |                      |             |
|  | 2711P-B10C15D1          | 2711P-B10C4D8 | +                    | 2711P-RN15S |
|  | 2711P-B10C15D2          |               |                      |             |
|  | 2711P-B10C15D6          | 2711P-B10C4D9 | +                    | 2711P-RN15S |
| 2711P-B10C15D7   |                         |               |                      |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-B10C4A1           | 2711P-B10C4A8 | +                    | —           |
|  | 2711P-B10C4A2           |               |                      |             |
|  | 2711P-B10C4A6           | 2711P-B10C4A9 | +                    | —           |
|  | 2711P-B10C4A7           |               |                      |             |
|  | 2711P-B10C4B1           | 2711P-B10C4A8 | +                    | —           |
|  | 2711P-B10C4B2           |               |                      |             |
|  | 2711P-B10C4D1           | 2711P-B10C4D8 | +                    | —           |
|  | 2711P-B10C4D2           |               |                      |             |
|  | 2711P-B10C4D6           | 2711P-B10C4D9 | +                    | —           |
| 2711P-B10C4D7  |                         |               |                      |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-B10C6A1           | 2711P-B10C4A8 | +                    | 2711P-RN6   |
|  | 2711P-B10C6A2           |               |                      |             |
|  | 2711P-B10C6A6           | 2711P-B10C4A9 | +                    | 2711P-RN6   |
|  | 2711P-B10C6A7           |               |                      |             |
|  | 2711P-B10C6B1           | 2711P-B10C4A8 | +                    | 2711P-RN6   |
|  | 2711P-B10C6B2           |               |                      |             |
|  | 2711P-B10C6D1           | 2711P-B10C4D8 | +                    | 2711P-RN6   |
|  | 2711P-B10C6D2           |               |                      |             |
|  | 2711P-B10C6D6           | 2711P-B10C4D9 | +                    | 2711P-RN6   |
| 2711P-B10C6D7  |                         |               |                      |             |

**Table 11 - Cat. No. Conversions for 1000 Terminal Models**

| <b>From Existing PanelView Plus/PanelView Plus CE</b>                    | <b>To New PanelView Plus 6</b> | <b>+</b>      | <b>Communication Module</b> |             |
|--|--------------------------------|---------------|-----------------------------|-------------|
| <b>1000 Touch-screen Terminals</b>                                       |                                |               |                             |             |
| Configured terminal with ControlNet communication                        | 2711P-T10C15A1                 | 2711P-T10C4A8 | +                           | 2711P-RN15S |
|  | 2711P-T10C15A2                 |               |                             |             |
|  | 2711P-T10C15A6                 | 2711P-T10C4A9 | +                           | 2711P-RN15S |
|  | 2711P-T10C15A7                 |               |                             |             |
|  | 2711P-T10C15B1                 | 2711P-T10C4A8 | +                           | 2711P-RN15S |
|  | 2711P-T10C15B2                 |               |                             |             |
|  | 2711P-T10C15D1                 | 2711P-T10C4D8 | +                           | 2711P-RN15S |
|  | 2711P-T10C15D2                 |               |                             |             |
|  | 2711P-T10C15D6                 | 2711P-T10C4D9 | +                           | 2711P-RN15S |
|  | 2711P-T10C15D7                 |               |                             |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-T10C4A1                  | 2711P-T10C4A8 | +                           | —           |
|  | 2711P-T10C4A2                  |               |                             |             |
|  | 2711P-T10C4A6                  | 2711P-T10C4A9 | +                           | —           |
|  | 2711P-T10C4A7                  |               |                             |             |
|  | 2711P-T10C4B1                  | 2711P-T10C4A8 | +                           | —           |
|  | 2711P-T10C4B2                  |               |                             |             |
|  | 2711P-T10C4D1                  | 2711P-T10C4D8 | +                           | —           |
|  | 2711P-T10C4D2                  |               |                             |             |
|  | 2711P-T10C4D6                  | 2711P-T10C4D9 | +                           | —           |
|  | 2711P-T10C4D7                  |               |                             |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-T10C6A1                  | 2711P-T10C4A8 | +                           | 2711P-RN6   |
|  | 2711P-T10C6A2                  |               |                             |             |
|  | 2711P-T10C6A6                  | 2711P-T10C4A9 | +                           | 2711P-RN6   |
|  | 2711P-T10C6A7                  |               |                             |             |
|  | 2711P-T10C6B1                  | 2711P-T10C4A8 | +                           | 2711P-RN6   |
|  | 2711P-T10C6B2                  |               |                             |             |
|  | 2711P-T10C6D1                  | 2711P-T10C4D8 | +                           | 2711P-RN6   |
|  | 2711P-T10C6D2                  |               |                             |             |
|  | 2711P-T10C6D6                  | 2711P-T10C4D9 | +                           | 2711P-RN6   |
|  | 2711P-T10C6D7                  |               |                             |             |

**Table 11 - Cat. No. Conversions for 1000 Terminal Models**

| <b>From Existing PanelView Plus/PanelView Plus CE</b>                    | <b>To New PanelView Plus 6</b> | <b>+</b>      | <b>Communication Module</b> |             |
|--|--------------------------------|---------------|-----------------------------|-------------|
| <b>1000 Keypad Terminals</b>   |                                |               |                             |             |
| Configured terminal with ControlNet communication                        | 2711P-K10C15A1                 | 2711P-K10C4A8 | +                           | 2711P-RN15S |
|  | 2711P-K10C15A2                 |               |                             |             |
|  | 2711P-K10C15A6                 | 2711P-K10C4A9 | +                           | 2711P-RN15S |
|  | 2711P-K10C15A7                 |               |                             |             |
|  | 2711P-K10C15B1                 | 2711P-K10C4A8 | +                           | 2711P-RN15S |
|  | 2711P-K10C15B2                 |               |                             |             |
|  | 2711P-K10C15D1                 | 2711P-K10C4D8 | +                           | 2711P-RN15S |
|  | 2711P-K10C15D2                 |               |                             |             |
|  | 2711P-K10C15D6                 | 2711P-K10C4D9 | +                           | 2711P-RN15S |
| 2711P-K10C15D7   |                                |               |                             |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-K10C4A1                  | 2711P-K10C4A8 | +                           | —           |
|  | 2711P-K10C4A2                  |               |                             |             |
|  | 2711P-K10C4A6                  | 2711P-K10C4A9 | +                           | —           |
|  | 2711P-K10C4A7                  |               |                             |             |
|  | 2711P-K10C4B1                  | 2711P-K10C4A8 | +                           | —           |
|  | 2711P-K10C4B2                  |               |                             |             |
|  | 2711P-K10C4D1                  | 2711P-K10C4D8 | +                           | —           |
|  | 2711P-K10C4D2                  |               |                             |             |
|  | 2711P-K10C4D6                  | 2711P-K10C4D9 | +                           | —           |
| 2711P-K10C4D7  |                                |               |                             |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-K10C6A1                  | 2711P-K10C4A8 | +                           | 2711P-RN6   |
|  | 2711P-K10C6A2                  |               |                             |             |
|  | 2711P-K10C6A6                  | 2711P-K10C4A9 | +                           | 2711P-RN6   |
|  | 2711P-K10C6A7                  |               |                             |             |
|  | 2711P-K10C6B1                  | 2711P-K10C4A8 | +                           | 2711P-RN6   |
|  | 2711P-K10C6B2                  |               |                             |             |
|  | 2711P-K10C6D1                  | 2711P-K10C4D8 | +                           | 2711P-RN6   |
|  | 2711P-K10C6D2                  |               |                             |             |
|  | 2711P-K10C6D6                  | 2711P-K10C4D9 | +                           | 2711P-RN6   |
| 2711P-K10C6D7  |                                |               |                             |             |

**Table 12 - Cat. No. Conversions for 1250 Terminal Models**

| <b>From Existing PanelView Plus/PanelView Plus CE</b>                    | <b>To New PanelView Plus 6</b> | <b>+</b>      | <b>Communication Module</b> |             |
|--|--------------------------------|---------------|-----------------------------|-------------|
| <b>1250 Keypad &amp; Touch-screen Terminals</b>                          |                                |               |                             |             |
| Configured terminal with ControlNet communication                        | 2711P-B12C15A1                 | 2711P-B12C4A8 | +                           | 2711P-RN15S |
|  | 2711P-B12C15A2                 |               |                             |             |
|  | 2711P-B12C15A6                 | 2711P-B12C4A9 | +                           | 2711P-RN15S |
|  | 2711P-B12C15A7                 |               |                             |             |
|  | 2711P-B12C15B1                 | 2711P-B12C4A8 | +                           | 2711P-RN15S |
|  | 2711P-B12C15B2                 |               |                             |             |
|  | 2711P-B12C15D1                 | 2711P-B12C4D8 | +                           | 2711P-RN15S |
|  | 2711P-B12C15D2                 |               |                             |             |
|  | 2711P-B12C15D6                 | 2711P-B12C4D9 | +                           | 2711P-RN15S |
| 2711P-B12C15D7   |                                |               |                             |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-B12C4A1                  | 2711P-B12C4A8 | +                           | —           |
|  | 2711P-B12C4A2                  |               |                             |             |
|  | 2711P-B12C4A6                  | 2711P-B12C4A9 | +                           | —           |
|  | 2711P-B12C4A7                  |               |                             |             |
|  | 2711P-B12C4B1                  | 2711P-B12C4A8 | +                           | —           |
|  | 2711P-B12C4B2                  |               |                             |             |
|  | 2711P-B12C4D1                  | 2711P-B12C4D8 | +                           | —           |
|  | 2711P-B12C4D2                  |               |                             |             |
|  | 2711P-B12C4D6                  | 2711P-B12C4D9 | +                           | —           |
| 2711P-B12C4D7  |                                |               |                             |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-B12C6A1                  | 2711P-B12C4A8 | +                           | 2711P-RN6   |
|  | 2711P-B12C6A2                  |               |                             |             |
|  | 2711P-B12C6A6                  | 2711P-B12C4A9 | +                           | 2711P-RN6   |
|  | 2711P-B12C6A7                  |               |                             |             |
|  | 2711P-B12C6B1                  | 2711P-B12C4A8 | +                           | 2711P-RN6   |
|  | 2711P-B12C6B2                  |               |                             |             |
|  | 2711P-B12C6D1                  | 2711P-B12C4D8 | +                           | 2711P-RN6   |
|  | 2711P-B12C6D2                  |               |                             |             |
|  | 2711P-B12C6D6                  | 2711P-B12C4D9 | +                           | 2711P-RN6   |
| 2711P-B12C6D7  |                                |               |                             |             |

**Table 12 - Cat. No. Conversions for 1250 Terminal Models**

| <b>From Existing PanelView Plus/PanelView Plus CE</b>                    | <b>To New PanelView Plus 6</b> | <b>+</b>       | <b>Communication Module</b> |             |
|--|--------------------------------|----------------|-----------------------------|-------------|
| <b>1250 Touch-screen Terminals</b>                                       |                                |                |                             |             |
| Configured terminal with ControlNet communication                        | 2711P-T12C15A1                 | 2711P-T12C4A8  | +                           | 2711P-RN15S |
|  | 2711P-T12C15A2                 |                |                             |             |
|  | 2711P-T12C15A6                 | 2711P-T12C4A9  | +                           | 2711P-RN15S |
|  | 2711P-T12C15A7                 |                |                             |             |
|  | 2711P-T12C15B1                 | 2711P-T12C4A8  | +                           | 2711P-RN15S |
|  | 2711P-T12C15B2                 |                |                             |             |
|  | 2711P-T12C15D1                 | 2711P-T12C4D8  | +                           | 2711P-RN15S |
|  | 2711P-T12C15D2                 |                |                             |             |
|  | 2711P-T12C15D6                 | 2711P-T12C4D9  | +                           | 2711P-RN15S |
| 2711P-T12C15D7   |                                |                |                             |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-T12C4A1                  | 2711P-T12C4A8  | +                           | —           |
|  | 2711P-T12C4A2                  |                |                             |             |
|  | 2711P-T12C4A6                  | 2711P-T12C4A9  | +                           | —           |
|  | 2711P-T12C4A7                  |                |                             |             |
|  | 2711P-T12C4B1                  | 2711P-T12C4A8  | +                           | —           |
|  | 2711P-T12C4B2                  |                |                             |             |
|  | 2711P-T12C4D2K                 | 2711P-T12C4D8K |                             | —           |
|  | 2711P-T12C4D6K                 |                |                             |             |
|  | 2711P-T12C4D1                  | 2711P-T12C4D8  | +                           | —           |
|  | 2711P-T12C4D2                  |                |                             |             |
|  | 2711P-T12C4D6                  | 2711P-T12C4D9  | +                           | —           |
| 2711P-T12C4D7  |                                |                |                             |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-T12C6A1                  | 2711P-T12C4A8  | +                           | 2711P-RN6   |
|  | 2711P-T12C6A2                  |                |                             |             |
|  | 2711P-T12C6A6                  | 2711P-T12C4A9  | +                           | 2711P-RN6   |
|  | 2711P-T12C6A7                  |                |                             |             |
|  | 2711P-T12C6B1                  | 2711P-T12C4A8  | +                           | 2711P-RN6   |
|  | 2711P-T12C6B2                  |                |                             |             |
|  | 2711P-T12C6D1                  | 2711P-T12C4D8  | +                           | 2711P-RN6   |
|  | 2711P-T12C6D2                  |                |                             |             |
| 2711P-T12C6D6  | 2711P-T12C4D9                  | +              | 2711P-RN6                   |             |
| 2711P-T12C6D7  |                                |                |                             |             |

**Table 12 - Cat. No. Conversions for 1250 Terminal Models**

| <b>From Existing PanelView Plus/PanelView Plus CE</b>                    | <b>To New PanelView Plus 6</b> | <b>+</b>      | <b>Communication Module</b> |             |
|--|--------------------------------|---------------|-----------------------------|-------------|
| <b>1250 Keypad Terminals</b>   |                                |               |                             |             |
| Configured terminal with ControlNet communication                        | 2711P-K12C15A1                 | 2711P-K12C4A8 | +                           | 2711P-RN15S |
|  | 2711P-K12C15A2                 |               |                             |             |
|  | 2711P-K12C15A6                 | 2711P-K12C4A9 | +                           | 2711P-RN15S |
|  | 2711P-K12C15A7                 |               |                             |             |
|  | 2711P-K12C15B1                 | 2711P-K12C4A8 | +                           | 2711P-RN15S |
|  | 2711P-K12C15B2                 |               |                             |             |
|  | 2711P-K12C15D1                 | 2711P-K12C4D8 | +                           | 2711P-RN15S |
|  | 2711P-K12C15D2                 |               |                             |             |
|  | 2711P-K12C15D6                 | 2711P-K12C4D9 | +                           | 2711P-RN15S |
|  | 2711P-K12C15D7                 |               |                             |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-K12C4A1                  | 2711P-K12C4A8 | +                           | —           |
|  | 2711P-K12C4A2                  |               |                             |             |
|  | 2711P-K12C4A6                  | 2711P-K12C4A9 | +                           | —           |
|  | 2711P-K12C4A7                  |               |                             |             |
|  | 2711P-K12C4B1                  | 2711P-K12C4A8 | +                           | —           |
|  | 2711P-K12C4B2                  |               |                             |             |
|  | 2711P-K12C4D1                  | 2711P-K12C4D8 | +                           | —           |
|  | 2711P-K12C4D2                  |               |                             |             |
|  | 2711P-K12C4D6                  | 2711P-K12C4D9 | +                           | —           |
|  | 2711P-K12C4D7                  |               |                             |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-K12C6A1                  | 2711P-K12C4A8 | +                           | 2711P-RN6   |
|  | 2711P-K12C6A2                  |               |                             |             |
|  | 2711P-K12C6A6                  | 2711P-K12C4A9 | +                           | 2711P-RN6   |
|  | 2711P-K12C6A7                  |               |                             |             |
|  | 2711P-K12C6B1                  | 2711P-K12C4A8 | +                           | 2711P-RN6   |
|  | 2711P-K12C6B2                  |               |                             |             |
|  | 2711P-K12C6D1                  | 2711P-K12C4D8 | +                           | 2711P-RN6   |
|  | 2711P-K12C6D2                  |               |                             |             |
|  | 2711P-K12C6D6                  | 2711P-K12C4D9 | +                           | 2711P-RN6   |
|  | 2711P-K12C6D7                  |               |                             |             |



**Table 13 - Cat. No. Conversions for 1500 Terminal Models**

| From Existing PanelView Plus/PanelView Plus CE                           | To New PanelView Plus 6 | +             | Communication Module |             |
|--|-------------------------|---------------|----------------------|-------------|
| <b>1500 Keypad &amp; Touch-screen Terminals</b>                          |                         |               |                      |             |
| Configured terminal with ControlNet communication                        | 2711P-B15C15A1          | 2711P-B15C4A8 | +                    | 2711P-RN15S |
|  | 2711P-B15C15A2          |               |                      |             |
|  | 2711P-B15C15A6          | 2711P-B15C4A9 | +                    | 2711P-RN15S |
|  | 2711P-B15C15A7          |               |                      |             |
|  | 2711P-B15C15B1          | 2711P-B15C4A8 | +                    | 2711P-RN15S |
|  | 2711P-B15C15B2          |               |                      |             |
|  | 2711P-B15C15D1          | 2711P-B15C4D8 | +                    | 2711P-RN15S |
|  | 2711P-B15C15D2          |               |                      |             |
|  | 2711P-B15C15D6          | 2711P-B15C4D9 | +                    | 2711P-RN15S |
| 2711P-B15C15D7   |                         |               |                      |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-B15C4A1           | 2711P-B15C4A8 | +                    | —           |
|  | 2711P-B15C4A2           |               |                      |             |
|  | 2711P-B15C4A6           | 2711P-B15C4A9 | +                    | —           |
|  | 2711P-B15C4A7           |               |                      |             |
|  | 2711P-B15C4B1           | 2711P-B15C4A8 | +                    | —           |
|  | 2711P-B15C4B2           |               |                      |             |
|  | 2711P-B15C4D1           | 2711P-B15C4D8 | +                    | —           |
|  | 2711P-B15C4D2           |               |                      |             |
|  | 2711P-B15C4D6           | 2711P-B15C4D9 | +                    | —           |
| 2711P-B15C4D7  |                         |               |                      |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-B15C6A1           | 2711P-B15C4A8 | +                    | 2711P-RN6   |
|  | 2711P-B15C6A2           |               |                      |             |
|  | 2711P-B15C6A6           | 2711P-B15C4A9 | +                    | 2711P-RN6   |
|  | 2711P-B15C6A7           |               |                      |             |
|  | 2711P-B15C6B1           | 2711P-B15C4A8 | +                    | 2711P-RN6   |
|  | 2711P-B15C6B2           |               |                      |             |
|  | 2711P-B15C6D1           | 2711P-B15C4D8 | +                    | 2711P-RN6   |
|  | 2711P-B15C6D2           |               |                      |             |
|  | 2711P-B15C6D6           | 2711P-B15C4D9 | +                    | 2711P-RN6   |
| 2711P-B15C6D7  |                         |               |                      |             |

**Table 13 - Cat. No. Conversions for 1500 Terminal Models**

| <b>From Existing PanelView Plus/PanelView Plus CE</b>                    | <b>To New PanelView Plus 6</b> | <b>+</b>      | <b>Communication Module</b> |             |
|--|--------------------------------|---------------|-----------------------------|-------------|
| <b>1500 Touch-screen Terminals</b>                                       |                                |               |                             |             |
| Configured terminal with ControlNet communication                        | 2711P-T15C15A1                 | 2711P-T15C4A8 | +                           | 2711P-RN15S |
|  | 2711P-T15C15A2                 |               |                             |             |
|  | 2711P-T15C15A6                 | 2711P-T15C4A9 | +                           | 2711P-RN15S |
|  | 2711P-T15C15A7                 |               |                             |             |
|  | 2711P-T15C15B1                 | 2711P-T15C4A8 | +                           | 2711P-RN15S |
|  | 2711P-T15C15B2                 |               |                             |             |
|  | 2711P-T15C15D1                 | 2711P-T15C4D8 | +                           | 2711P-RN15S |
|  | 2711P-T15C15D2                 |               |                             |             |
|  | 2711P-T15C15D6                 | 2711P-T15C4D9 | +                           | 2711P-RN15S |
|  | 2711P-T15C15D7                 |               |                             |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-T15C4A1                  | 2711P-T15C4A8 | +                           | —           |
|  | 2711P-T15C4A2                  |               |                             |             |
|  | 2711P-T15C4A6                  | 2711P-T15C4A9 | +                           | —           |
|  | 2711P-T15C4A7                  |               |                             |             |
|  | 2711P-T15C4B1                  | 2711P-T15C4A8 | +                           | —           |
|  | 2711P-T15C4B2                  |               |                             |             |
|  | 2711P-T15C4D1                  | 2711P-T15C4D8 | +                           | —           |
|  | 2711P-T15C4D2                  |               |                             |             |
|  | 2711P-T15C4D6                  | 2711P-T15C4D9 | +                           | —           |
|  | 2711P-T15C4D7                  |               |                             |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-T15C6A1                  | 2711P-T15C4A8 | +                           | 2711P-RN6   |
|  | 2711P-T15C6A2                  |               |                             |             |
|  | 2711P-T15C6A6                  | 2711P-T15C4A9 | +                           | 2711P-RN6   |
|  | 2711P-T15C6A7                  |               |                             |             |
|  | 2711P-T15C6B1                  | 2711P-T15C4A8 | +                           | 2711P-RN6   |
|  | 2711P-T15C6B2                  |               |                             |             |
|  | 2711P-T15C6D1                  | 2711P-T15C4D8 | +                           | 2711P-RN6   |
|  | 2711P-T15C6D2                  |               |                             |             |
|  | 2711P-T15C6D6                  | 2711P-T15C4D9 | +                           | 2711P-RN6   |
|  | 2711P-T15C6D7                  |               |                             |             |

**Table 13 - Cat. No. Conversions for 1500 Terminal Models**

| <b>From Existing PanelView Plus/PanelView Plus CE</b>                    | <b>To New PanelView Plus 6</b> | <b>+</b>      | <b>Communication Module</b> |             |
|--|--------------------------------|---------------|-----------------------------|-------------|
| <b>1500 Keypad Terminals</b>   |                                |               |                             |             |
| Configured terminal with ControlNet communication                        | 2711P-K15C15A1                 | 2711P-K15C4A8 | +                           | 2711P-RN15S |
|  | 2711P-K15C15A2                 |               |                             |             |
|  | 2711P-K15C15A6                 | 2711P-K15C4A9 | +                           | 2711P-RN15S |
|  | 2711P-K15C15A7                 |               |                             |             |
|  | 2711P-K15C15B1                 | 2711P-K15C4A8 | +                           | 2711P-RN15S |
|  | 2711P-K15C15B2                 |               |                             |             |
|  | 2711P-K15C15D1                 | 2711P-K15C4D8 | +                           | 2711P-RN15S |
|  | 2711P-K15C15D2                 |               |                             |             |
|  | 2711P-K15C15D6                 | 2711P-K15C4D9 | +                           | 2711P-RN15S |
| 2711P-K15C15D7   |                                |               |                             |             |
| Base unit terminal with built-in Ethernet and RS-232 communication ports | 2711P-K15C4A1                  | 2711P-K15C4A8 | +                           | —           |
|  | 2711P-K15C4A2                  |               |                             |             |
|  | 2711P-K15C4A6                  | 2711P-K15C4A9 | +                           | —           |
|  | 2711P-K15C4A7                  |               |                             |             |
|  | 2711P-K15C4B1                  | 2711P-K15C4A8 | +                           | —           |
|  | 2711P-K15C4B2                  |               |                             |             |
|  | 2711P-K15C4D1                  | 2711P-K15C4D8 | +                           | —           |
|  | 2711P-K15C4D2                  |               |                             |             |
|  | 2711P-K15C4D6                  | 2711P-K15C4D9 | +                           | —           |
| 2711P-K15C4D7  |                                |               |                             |             |
| Configured terminal with DH+ /DH-485 communication                       | 2711P-K15C6A1                  | 2711P-K15C4A8 | +                           | 2711P-RN6   |
|  | 2711P-K15C6A2                  |               |                             |             |
|  | 2711P-K15C6A6                  | 2711P-K15C4A9 | +                           | 2711P-RN6   |
|  | 2711P-K15C6A7                  |               |                             |             |
|  | 2711P-K15C6B1                  | 2711P-K15C4A8 | +                           | 2711P-RN6   |
|  | 2711P-K15C6B2                  |               |                             |             |
|  | 2711P-K15C6D1                  | 2711P-K15C4D8 | +                           | 2711P-RN6   |
|  | 2711P-K15C6D2                  |               |                             |             |
|  | 2711P-K15C6D6                  | 2711P-K15C4D9 | +                           | 2711P-RN6   |
| 2711P-K15C6D7  |                                |               |                             |             |

## Logic Module Conversions

This table converts logic modules used by the PanelView Plus and PanelView Plus CE terminals to the new logic modules used by the PanelView Plus 6 terminals.

**Table 14 - Cat. No. Conversions - Logic Modules**

| From PanelView Plus and CE Logic Modules | To New PanelView Plus 6 Logic Modules | Description   |
|--|---------------------------------------|---|
| 2711P-RP                                 | 2711P-RP8D                            | <ul style="list-style-type: none"> <li>Terminals without extended features and file viewers</li> <li>DC isolated input power</li> </ul>                           |
| 2711P-RP1                                |                                       |   |
| 2711P-RP1D                               |                                       |   |
| 2711P-RP2                                |                                       |   |
| 2711P-RP2D                               |                                       |   |
| 2711P-RP3                                |                                       |   |
| 2711P-RP3D                               |                                       |   |
| 2711P-RPA                                | 2711P-RP8A                            | <ul style="list-style-type: none"> <li>Terminals without extended features and file viewers</li> <li>AC input power</li> </ul>                                    |
| 2711P-RP1A                               |                                       |   |
| 2711P-RP2A                               |                                       |   |
| 2711P-RP3A                               |                                       |   |
| 2711P-RP2DK                              | 2711P-RP8DK                           | <ul style="list-style-type: none"> <li>Terminals without extended features and file viewers</li> <li>DC isolated input power</li> <li>Conformal coated</li> </ul> |
| 2711P-RP2K                               |                                       |   |
| 2711P-RP6                                | 2711P-RP9D                            | <ul style="list-style-type: none"> <li>Terminals with extended features and file viewers</li> <li>DC isolated input power</li> </ul>                              |
| 2711P-RP6D                               |                                       |   |
| 2711P-RP7                                |                                       |   |
| 2711P-RP7D                               |                                       |   |
| 2711P-RP6A                               | 2711P-RP9A                            | <ul style="list-style-type: none"> <li>Terminals with extended features and file viewers</li> <li>AC input power</li> </ul>                                       |
| 2711P-RP7A                               |                                       |   |
| 2711P-RP6DK                              | 2711P-RP9DK                           | <ul style="list-style-type: none"> <li>Terminals with extended features and file viewers</li> <li>DC isolated input power</li> <li>Conformal coated</li> </ul>    |
| 2711P-RP6K                               |                                       |   |

## Additional Resources

These documents contain additional information concerning related products from Rockwell Automation.

| Resource  | Description  |
|---|--|
| Visualization Selection Guide, publication <a href="#">VIEW-SG001</a>                       | Provides an overview and selection tool for the operator interface platforms, including the PanelView Plus 6 terminals.                              |
| PanelView Plus Specifications Technical Data, publication <a href="#">2711P-TD005</a>       | Provides certifications, environmental, and technical specifications for the operator interface platforms, including the PanelView Plus 6 terminals. |
| Industrial Automation Wiring and Grounding Guidelines, publication <a href="#">1770-4.1</a> | Provides general guidelines for installing a Rockwell Automation industrial system.  |
| Product Certifications website, <a href="http://www.ab.com">http://www.ab.com</a>           | Provides declarations of conformity, certificates, and other certification details.  |

You can view or download publications at <http://www.rockwellautomation.com/literature/>. To order paper copies of technical documentation, contact your local Allen-Bradley distributor or Rockwell Automation sales representative.



[www.klinkmann.com](http://www.klinkmann.com)

**Helsinki**  
tel. +358 9 540 4940  
[automation@klinkmann.fi](mailto:automation@klinkmann.fi)

**St. Petersburg**  
tel. +7 812 327 3752  
[klinkmann@klinkmann.spb.ru](mailto:klinkmann@klinkmann.spb.ru)

**Moscow**  
tel. +7 495 641 1616  
[moscow@klinkmann.spb.ru](mailto:moscow@klinkmann.spb.ru)

**Yekaterinburg**  
tel. +7 343 376 5393  
[yekaterinburg@klinkmann.spb.ru](mailto:yekaterinburg@klinkmann.spb.ru)

**Samara**  
tel. +7 846 273 95 85  
[samara@klinkmann.spb.ru](mailto:samara@klinkmann.spb.ru)

**Kiev**  
tel. +38 044 495 33 40  
[klinkmann@klinkmann.kiev.ua](mailto:klinkmann@klinkmann.kiev.ua)

**Riga**  
tel. +371 6738 1617  
[klinkmann@klinkmann.lv](mailto:klinkmann@klinkmann.lv)

**Vilnius**  
tel. +370 5 215 1646  
[post@klinkmann.lt](mailto:post@klinkmann.lt)

**Tallinn**  
tel. +372 668 4500  
[klinkmann.est@klinkmann.ee](mailto:klinkmann.est@klinkmann.ee)

**Minsk**  
tel. +375 17 200 0876  
[minsk@klinkmann.com](mailto:minsk@klinkmann.com)